

Control Systems

GANC-R-CH4

GANPRO 4

- 240VAC ON/OFF receiver with 4 outputs, protected by fuse for the control of resistive loads up to 4000W in total
- Programmable relay ON/OFF functions
- Independent or synchronised activation of relays that can be controlled from a single transmitter
- Possibility to memorise up to 42 transmitters

Features

- ON/OFF or impulsive controls
- Direct connection of the load to the relay
- Suitable for gardens and external surfaces
- Outputs: 4 x 10A outputs with fuse protection to directly connect load up to 2000W per output and 4000W in total
- Single or group commands are possible

Technical Specifications

- Power supply: 240VAC
- Number of outputs: 4
- Maximum power in total: 4000W
- Protection rating: IP54
- Dimensions: 180mm x 200mm x 79mm

Specification

- 4 Channel receiver
- 4 Channel wall transmitter
- 4 Channel key fob transmitter



Optional Extras



1 Channel Wall Transmitter
GANC-R-1WT



2 Channel Wall Transmitter
GANC-R-2WT



4 Channel Wall Transmitter
GANC-R-4WT



4 Channel Key Fob Transmitter
GANC-R-4KFT

MELBOURNE

1316 Malvern Road
 Malvern VIC 3144
 T 03 9824 4937
 vic@gan.com.au

SYDNEY

88 Alexander Street
 Crows Nest NSW 2065
 T 02 9439 9155
 nsw@gan.com.au

Specifications subject to change without notice